

A Unit of Electro Switch Corp.

Wire-In Photocontrol **Hazardous Location Unit**

Exclusive Feature

Dust-ignition proof

Explosion proof

Weatherproof

Tamper Resistant

Tempered Glass Lens 3/8" thick

Double-Sided
Plated-Through
Circuit Board (DSPT)
for durability and reliability

Quad-Gate Technology for precision and consistency

Full Wave Rectification

Dual Zener Diodes

320 Joule MOV

Solid Brass Contact Blades

Internal and External Ground
Screws Standard

Meets or exceeds rigid quality requirements of applicable ANSI C136.10, and C136.24 and C136.41

Phone: (803) 939-4700 Fax: (803) 939-4777

Email: info@RipleyLightingControls.com


www.RipleyLightingControls.com



Outdoor Lighting Control For Exterior Lighting In Hazardous Locations

Tank Farm Lighting
Building Perimeter Lighting
Exterior Process Lighting
Loading/Unloading Rack Lighting

	86390HL
Nominal Voltage 60 Hz	120/208/240/277
Voltage Range	105—305
Fail Mode	On
Load Rating	1000 Watt Tungsten / 1800 VA Ballast
Operating Temperature	-40C to +70C (-40F to +158F)
Photocell	Encapsulated Silicon Phototransistor
Dielectric Strength	5000 Volts between current carrying parts and metal surfaces
Surge Protection	320 Joule MOV / 10,000 amp surge current
Power Consumption	0.5 watts @ 120 V
Time Delay Off (Instant On)	3 to 5 seconds
Operating Light Levels (Standard Settings)	Turn On 1.5 FC ± .25 / Turn Off by 2.25 FC (Off:On Ratio = 1.5:1)
Housing	Sand cast copper-free aluminum - epoxy powder coated
Gasket	Neoprene O-ring
Wiring Connections	3 #14 AWG Stranded
	Option Code 1 (Add to end of Model Number)
Denotes Turn On point in FC	Specify 0.3—5.0 FC



Certifications and Compliances:

UL Classified
CSA Certified
FM Approved for:
Class I, Div 1 & 2, Group B, C, D*
Class II, Div 1 & 2, Group E, F, G
Class III

Nema 3, 4, 7 BCD*, 9 EFG Cenelec EEx d II B IP66

* When sealed within 18" of unit as per NEC Sections 501-5 and 502-5



Example Order #: 86390HL-1.0 signifies a 86390HL Hazardous Location Photocontrol with a Turn On setting of 1.0 FC

© 2021 by Ripley Lighting Controls, a Unit of Electroswitch. All rights reserved. The information in this document is provided for informational use only and is subject to change without notice.